

# IndoorCam

Indoor Wi-Fi security camera with PIR motion detector and built-in AI

Video stream	<p><b>Camera</b> 4 MP CMOS sensor</p> <p><b>Resolution</b> up to 2688 × 1520 px</p> <p><b>Camera viewing angles</b> horizontal: 110° vertical: 60°</p> <p><b>Video protocol</b> JetSparrow Fast and encrypted peer-to-peer video protocol developed by Ajax Systems.</p> <p><b>Storage options</b> Ajax Cloud (coming soon) NVR</p> <p><b>Video codec</b> H.264</p> <p><b>Dynamic range</b> HDR Improves the accuracy of detail in bright and dark scenes.</p>
Communication channel	<p><b>Wi-Fi</b> 802.11 b/g/n module 2.4 GHz, up to 2 Mbit/s for the channel 2K video.</p> <p><b>Jeweller and Wings communication technologies</b> Proprietary wireless communication technologies to transmit commands, alarms, events, and photo verifications. They serve as a backup communication channel when the device is added to the hub.</p>
Key features	<p><b>Two-way communication</b> Clear and loud voice communication between users and the device.</p> <p><b>Motion detection</b> The device detects movement using a built-in PIR sensor and software image frame analysis.</p> <p><b>Object detection</b> using AI</p> <ul style="list-style-type: none"><li>• People.</li><li>• Pets.</li><li>• Vehicles.</li></ul>

	<p><b>Smart IR illumination</b> up to 8 m up to 26 ft Automatic adjustment of intensity in real time to avoid overexposure. This allows you to see objects that are far away or too close to the camera in low-light conditions.</p> <p><b>Visual verification of Ajax alarms</b> The system allows you to set up a scenario when Ajax detectors activate selected cameras to start recording. The result is immediately sent to the mobile or desktop monitoring app.</p> <p><b>Microphone</b> For two-way communication and sound recording at the site.</p> <p><b>Speaker volume</b> up to XX dB XX dB at a distance of 1 m. XX dB at a distance of 3.3 ft.</p> <p><b>Audio codec</b> G722</p> <p><b>Audio processing</b> Always active noise suppression and echo cancellation.</p> <p><b>LED indication</b> An LED indicator shows the actual state of the device.</p>
PIR detection	<p><b>Sensitive elements</b> 1 × PIR sensor</p> <p><b>Motion detection distance</b> up to 4 m up to 13 ft Depends on the sensitivity level adjusted in the device settings.</p> <p><b>Motion detection angle</b> horizontal: 110° vertical: 60°</p> <p><b>Sensitivity</b> 3 levels Adjusted by a PRO or a user with admin rights in Ajax apps.</p>
Installation recommendations	<p>It is recommended to install the device at a height of XX m. It is recommended to install the device at a height of XX ft.</p> <p>The device is designed for indoor use only.</p> <p>It is <b>not recommended</b> to install the device in direct sunlight. This may cause overheating and damage to the device's electrical components.</p>

Sabotage protection	<p><b>Holding screw</b> secures the device on the mounting bracket</p> <p><b>mTLS</b> Encrypted connection for data protection.</p> <p><b>Authentication</b> via Ajax Cloud Without local access rights.</p> <p><b>Secure Boot</b> Protection against firmware spoofing.</p> <p><b>OTA signature verification</b> Secure automatic firmware update.</p> <p><b>Privacy</b> Access rights distribution for users in mobile apps and for monitoring operators in PRO Desktop.</p> <p><b>Communication loss detection</b> Wi-Fi: can be set from 30 s Jeweller/Wings: after 36 s Detection time depends on <b>Ajax Cloud connection</b> and <b>Jeweller</b> or <b>Jeweller/Fibra</b> settings.</p>
Power supply	<p><b>Power supply unit</b> 12 V<math>\pm</math> 20%, 1 A</p> <p><b>Device power consumption</b> TBC</p>
Enclosure	<p><b>Dimensions</b> 128 × 74 × 76 mm 5.04" × 2.91" × 2.99"</p> <p><b>Weight</b> 235 g 8.29 oz</p> <p><b>Operating temperature range</b> from 0 °C to +40 °C from 32 °F to 104 °F</p> <p><b>Operating humidity</b> up to 90% with no condensation</p> <p><b>Protection class</b> IP20</p>
Color	<p><b>White</b> RAL 9003</p>

	<b>Black</b> RAL 9005
<b>Complete set</b>	IndoorCam Power supply unit Installation kit Quick start guide
<b>Warranty</b>	24 months